tehnoteka

https://cenoteka.rs

Uputstvo za upotrebu (EN)

MSI zakrivljeni monitor 34'' MPG 341CQR QD-OLED X36

msi



Cenoteka je online destinacija za upoređivanje cena i karakteristika bele tehnike, potrošačke elektronike i IT uređaja kod trgovinskih lanaca i internet prodavnica u Srbiji. Naša stranica vam omogućava da istražite najnovije informacije, detaljne karakteristike i konkurentne cene proizvoda.

Posetite nas i uživajte u ekskluzivnom iskustvu pametne kupovine klikom na link:

https://cenoteka.rs/p/msi-zakrivljeni-monitor-34-mpg-341cqr-qd-oled-x36/



MPG Series

OLED Monitor

MPG 341CQR QD-OLED X36 (3DE2)

User Guide

Contents

Getting Started 3
- Package Contents 3
- Installing the Monitor Stand 4
- Adjusting the Monitor 5
- Monitor Overview 6
- Connecting the Monitor to PC 9

OSD Setup 11
- Navi Key 11
- Hot Key 11

OSD Menus 12
- AI Navigator 13
- Gaming Features 15
- Mode 18
- Input Source 19
- PIP/PBP 20
- MSI OLED Care 21
- General 23

Specifications 25

Preset Display Modes 27

Troubleshooting 30

Safety Instructions 31

TÜV Rheinland Certification 33

Regulatory Notices 34

Revision

V1.0, 2026/01

Getting Started

This chapter provides you with the information on hardware setup procedures. While connecting devices, be careful in holding the devices and use a grounded wrist strap to avoid static electricity.

Package Contents


Monitor	MPG 341CQR QD-OLED X36
Documentation	Quick Start Guide
Accessories	Stand
	Stand Base with Screw(s)
	Screw(s) for Wall Mount Bracket(s)
	Power Cord
	MSI PI Logo Sticker
	Fiber Cloth
	Color Report (Online Calibration Report)
Cables	Ultra High Speed HDMI™ Cable (Optional)
	DisplayPort Cable (Optional)
	USB Upstream Cable (Optional) (for USB Type-B Upstream Port)

Important

- *Contact your place of purchase or local distributor if any of the items is damaged or missing.*
- *Package contents may vary by country and model.*
- *The included power cord is exclusively for this monitor and should not be used with other products.*

Installing the Monitor Stand

1. Leave the monitor in its protective packaging. Align the stand to the monitor groove.
2. Push the stand towards the monitor groove until it locks in place.
3. Connect the base to the stand and tighten the base screw to secure the base.
4. Make sure the stand assembly is properly installed before setting the monitor upright.



Important


- *Place the monitor on a soft, protected surface to avoid scratching the display panel.*
- *Do not use any sharp objects on the panel.*
- *The groove for installing the stand bracket can also be used for wall mount. Please contact your dealer for proper wall mount kit.*


Adjusting the Monitor


This monitor is designed to maximize your viewing comfort with its adjustment capabilities.


Important

- *Avoid touching the display panel when adjusting the monitor.*
- *Please slightly tilt the monitor backwards before pivoting it.*










Monitor Overview



1	**AI Care Sensor**
2	**Power LED** Lit in white after the monitor is turned on. If no signal input, the LED will turn into orange. Lit in orange when the monitor is in Stand-by mode.
3	**Kensington Lock**
4	**Power Jack**
5	**G Key** To activate the OSD Application.
6	**Navi Key**
7	**Power Button**
8	**Headphone Jack**
9	**HDMI™ Connector** Supports HDMI™ CEC, 3440x1440@360Hz as specified in HDMI™ 2.1. ***Important*** *To ensure optimal performance and compatibility, please use only HDMI™ cables certified with the official HDMI™ logo when connecting this monitor. For more information, please visit https://www.hdmi.org/resource/cables.*
10	**HDMI™ Connector** Supports 3440x1440@360Hz as specified in HDMI™ 2.1. ***Important*** *To ensure optimal performance and compatibility, please use only HDMI™ cables certified with the official HDMI™ logo when connecting this monitor. For more information, please visit https://www.hdmi.org/resource/cables.*
11	**DisplayPort** Supports 3440x1440@360Hz as specified in DisplayPort 2.1a.

12 **USB Type-C Port**

This port supports DisplayPort Alternate (DP Alt) Mode and up to 20V/4.9A (98W) power delivery.

Important

Your USB-C signal source and cable must support DisplayPort Alternate Mode to enable video output to the monitor.


USB Type-C Power Delivery
5V / 3A (15W)
9V / 3A (27W)
12V / 3A (36W)
15V / 3A (45W)
20V / 4.9A (98W)

13 **USB 5Gbps Type-B Upstream Port**

For USB Upstream Cable.

Important

Check the package for USB Upstream Cable and connect it to the PC and monitor. Once this cable is connected, the USB Type-A Downstream Ports on the monitor will be ready for use.




14 **USB 5Gbps Type-A Port**

This connector is provided for USB peripheral devices. (Speed up to 5 Gbps)


15 **Cable Routing Hole**

Connecting the Monitor to PC


1. Connect the monitor to your computer with the video cable.



2. Plug in the monitor's power cable.




3. Turn on the monitor and your computer.



Important

Please remove the protective films from the display panel and ventilation ports before use to optimize performance and prevent overheating.



OSD Setup


This chapter provides you with essential information on OSD Setup.

Important

All information is subject to change without prior notice.

Navi Key

The monitor comes with a Navi Key, a multi-directional control that helps navigate the On-Screen Display (OSD) menu.



Up/Down/Left/Right:

- selecting function menus and items
- adjusting function values
- entering into/exiting from function menus


Press (OK):

- launching the On-Screen Display (OSD)
- entering submenus
- confirming a selection or setting

Hot Key

- Users may enter into preset function menus by moving the Navi Key up, down, left or right when the OSD menu is inactive.
- Users may customize their own Hot Keys to enter into different function menus.

OSD Menus



Important

The following settings will be grayed out when HDR signals are received:

- *AI Vision*
- *Low Blue Light*
- *Brightness*
- *Contrast*
- *Color Temperature*
- *Optix Scope*
- *PIP, PBP*
- *AI Light Sensor*
- *AI Brightness*
- *Adaptive DIM*
- *Gamma*
- *Six-Axis Color*
- *Saturation*
- *sRGB*
- *Adobe RGB*
- *Display P3*
- *Black-White*

AI Navigator

Feature	Available Settings		Description
AI Crosshair	OFF		• Through AI algorithm, this function enhances the visibility of in-game crosshair. • Users can select the color, size and position of the crosshair.
	ON		
	Icon	1/2/3/4/5/6/7/8	
	Icon Colors	Adaptive	
		Customize	
		R (0-255)	
		G (0-255)	
		B (0-255)	
	Icon Size	x0.5	
		x1.0	
		x1.5	
	Position		
	Position Reset		
AI Vision	OFF		• AI Vision enhances image quality by optimizing the contrast of images and background brightness.
	Level 1		
	Level 2		
	Level 3		
	Level 4		
	Level 5		

<table>
<tr><th>Feature</th><th colspan="3">Available Settings</th><th>Description</th></tr>
<tr><td rowspan="11">AI Care Sensor</td><td colspan="3">OFF</td><td rowspan="2">• This feature enables AI-based human detection features.</td></tr>
<tr><td colspan="3">ON</td></tr>
<tr><td rowspan="2">Active Mode</td><td colspan="2">System Mode</td><td rowspan="2">• When set to System Mode, WoA, LoL, and Adaptive DIM are controlled via the Microsoft Windows® operating system.
• When set to Monitor Mode, WoA, LoL, and Adaptive DIM are controlled via the monitor's OSD menu.</td></tr>
<tr><td colspan="2">Monitor Mode</td></tr>
<tr><td rowspan="3">Wake on Approach</td><td colspan="2">OFF</td><td rowspan="2">• WoA (Wake on Approach) is grayed out when Active Mode is set to System Mode.
• When WoA is set to ON, the monitor automatically wakes upon detecting a nearby user.</td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td>Timer Setting</td><td>0-30</td><td>• Users can set a timer from 0 to 30 seconds.
• Setting to 0 activates the function immediately.</td></tr>
<tr><td rowspan="3">Lock on Leave</td><td colspan="2">OFF</td><td rowspan="2">• LoL (Lock on Leave) is grayed out when Active Mode is set to System Mode.
• When LoL is set to ON, the monitor automatically locks upon detecting that the user has left.</td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td>Timer Setting</td><td>10-120</td><td>• Users can set a timer from 10 to 120 seconds.</td></tr>
<tr><td rowspan="2">Adaptive DIM</td><td colspan="2">OFF</td><td rowspan="2">• Adaptive DIM is grayed out when Active Mode is set to System Mode.
• When Adaptive DIM is set to ON, the monitor automatically dims the screen when it detects that the user has looked away.
• Activating Adaptive DIM will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» AI Brightness</td><td>Set to OFF</td></tr></table></td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="3">AI Brightness</td><td colspan="3">OFF</td><td rowspan="3">• Through the internal Light Sensor and AI (Artificial Intelligence) algorithm, this function detects the ambient light and automatically sets the monitor to optimal brightness for users.
• Customize allows users to adjust the auto brightness curve.
• Activating AI Brightness will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» Adaptive DIM</td><td>Set to OFF</td></tr><tr><td>» Brightness</td><td>Unable to select</td></tr></table></td></tr>
<tr><td colspan="3">Auto</td></tr>
<tr><td>Customize</td><td colspan="2">0-100</td></tr>
</table>

<table>
<tr><th>Feature</th><th>Available Settings</th><th>Description</th></tr>
<tr><td>AI Light Sensor</td><td>OFF
ON</td><td>• Through the internal RGB Sensor and AI algorithm, this function detects the ambient color temperature and presents the best light effects synced to the environment.
• Activating AI Light Sensor will affect:<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» Contrast
» Color Temperature
» Low Blue Light
» sRGB, Adobe RGB, Display P3 Mode</td><td>Unable to select</td></tr></table></td></tr>
</table>

Gaming Features

<table>
<tr><th>Feature</th><th colspan="2">Available Settings</th><th>Description</th></tr>
<tr><td>KVM</td><td rowspan="4">Type B</td><td>HDMI™ 1</td><td rowspan="9">• The KVM function allows users to control multiple devices, such as a gaming PC, laptop, or console, using a single set of keyboard and mouse connected to the monitor's USB ports.
• Only one USB control path can be active at a time — choose either Upstream or Type-C.</td></tr>
<tr><td>HDMI™ 2</td></tr>
<tr><td>DP</td></tr>
<tr><td>Type C</td></tr>
<tr><td></td><td rowspan="4">Type C</td><td>HDMI™ 1</td></tr>
<tr><td></td><td>HDMI™ 2</td></tr>
<tr><td></td><td>DP</td></tr>
<tr><td></td><td>Type C</td></tr>
<tr><td>MPRT</td><td colspan="2">OFF
ON</td><td>• MPRT is available when the refresh rate is over 240Hz and 360Hz.
• Activating MPRT will affect:<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» Adaptive-Sync</td><td>Set to OFF</td></tr></table></td></tr>
<tr><td>Optix Scope</td><td colspan="2">OFF
ON</td><td rowspan="5">• The center point will zoom in when Optix Scope is enabled.
• AI Crosshair and Optix Scope can be enabled at the same time.
• Activating Optix Scope will affect:<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» Adaptive-Sync
» PIP/PBP
» Screen Size</td><td>Set to OFF</td></tr></table></td></tr>
<tr><td></td><td rowspan="4">Scope Ratio</td><td>x1.5</td></tr>
<tr><td></td><td>x2.0</td></tr>
<tr><td></td><td>x2.5</td></tr>
<tr><td></td><td>x3</td></tr>
</table>

<table>
<tr><th>Feature</th><th colspan="2">Available Settings</th><th>Description</th></tr>
<tr><td rowspan="6">DisplayHDR</td><td colspan="2">True Black 500</td><td rowspan="6">• The DisplayHDR function enhances visuals with customizable settings for optimized brightness and contrast.
• Users can adjust HDR Customization using the Navi key.
• Adjustable HDR curves for True Black 500 and Peak 1300 nits are saved separately.</td></tr>
<tr><td colspan="2">Peak 1300 nits</td></tr>
<tr><td colspan="2">EOTF Boost</td></tr>
<tr><td colspan="2">Cust. (True Black 500)</td></tr>
<tr><td colspan="2">Cust. (Peak 1300)</td></tr>
<tr><td>HDR Brightness</td><td>0-100</td></tr>
<tr><td rowspan="2">DSC</td><td colspan="2">OFF</td><td rowspan="2">• For more DSC timing information, please check Preset Display Modes for DSC ON/OFF timing tables.
• Activating DSC will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» PIP/PBP</td><td>Unable to select</td></tr></table></td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="2">HDMI™ 2.1</td><td colspan="2">PC</td><td rowspan="2">• The Console mode offers broader compatibility with more console devices.
• Activating HDMI™ 2.1 will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» PIP/PBP</td><td>Set to OFF</td></tr></table></td></tr>
<tr><td colspan="2">Console</td></tr>
<tr><td rowspan="2">Adaptive-Sync</td><td colspan="2">OFF</td><td rowspan="2">• Adaptive-Sync prevents screen tearing.
• HDMI™ VRR (Variable Refresh Rate) synchronizes with Adaptive-Sync (ON/ OFF) and is disabled when Screen Size 1:1 is set to ON.
• Activating Adaptive-Sync will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» MPRT
» Optix Scope
» PIP/PBP</td><td>Set to OFF</td></tr><tr><td>» Screen Size</td><td>Set to Auto</td></tr></table></td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="10">Timer</td><td colspan="2">OFF</td><td rowspan="10">• After setting the time, press the OK Button to activate the timer.
• Users have to manually restore their preset Timer after any AC power loss and reconnection.</td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="4">Time Adjust</td><td>15:00</td></tr>
<tr><td>30:00</td></tr>
<tr><td>45:00</td></tr>
<tr><td>60:00</td></tr>
<tr><td rowspan="5">Show On</td><td>Left Top</td></tr>
<tr><td>Right Top</td></tr>
<tr><td>Left Bottom</td></tr>
<tr><td>Right Bottom</td></tr>
<tr><td>Customize</td></tr>
</table>

<table>
<tr><th>Feature</th><th colspan="2">Available Settings</th><th>Description</th></tr>
<tr><td rowspan="7">Refresh Rate</td><td colspan="2">OFF</td><td rowspan="7">• Location is adjustable in OSD Menu. Press the OK Button to confirm and apply your Refresh Rate Location.
• This monitor follows and works at the Operating System's preset Screen Refresh Rate.</td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="5">Show On</td><td>Left Top</td></tr>
<tr><td>Right Top</td></tr>
<tr><td>Left Bottom</td></tr>
<tr><td>Right Bottom</td></tr>
<tr><td>Customize</td></tr>
<tr><td rowspan="4">Screen Size</td><td colspan="2">Auto</td><td rowspan="4">• Users can adjust Screen Size in any mode, any resolution and any screen refresh rate.
• Activating Screen Size 1:1 will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» Adaptive-Sync
» PIP/PBP
» Optix Scope</td><td>Set to OFF</td></tr></table>
Important
Screen Size 1:1 refers to displaying content at its original resolution. This option is disabled when the monitor is set to its native resolution.</td></tr>
<tr><td colspan="2">4:3 (Forced)</td></tr>
<tr><td colspan="2">16:9 (Forced)</td></tr>
<tr><td colspan="2">21:9 (Forced)
1:1 (by pixel)</td></tr>
</table>

Mode

Mode	
» Eco	» RPG
» User	» Black-White
» Premium Color	» sRGB
» FPS	» Adobe RGB
» Racing	» Display P3
» RTS	

- Use Up or Down Button to select and preview mode effects.
- Press the OK Button to confirm and apply your mode type.
- The default setting "Eco" mode meets the requirements of TUV Rheinland's "Low Blue Light" standard.

- Activating FPS will affect:

Affected Function	Function Status
» Saturation	Unable to select

- Activating Black-White will affect:

Affected Function	Function Status
» Saturation » Six-Axis Color	Unable to select

- Activating sRGB, Adobe RGB, and Display P3 will affect:

Affected Function	Function Status
» AI Light Sensor » AI Brightness	Set to OFF & unable to select
» Contrast » Saturation » Six-Axis Color » Color Temperature: Customize » Low Blue Light	Unable to select

Feature	Available Settings	Description
Brightness	0-100	• Properly adjust Brightness according to the surrounding lighting.
Contrast	0-100	• Properly adjust Contrast to relax your eyes.
Sharpness	0-5	• Sharpness improves clarity and details of images.
Image Enhancement	OFF	• Image Enhancement enhances image edges to improve their acutance.
	Level 1	
	Level 2	
	Level 3	
	Level 4	
	Level 5	
Color Temperature	5000K	• This feature adjusts the overall color tone of the display. • Users can fine-tune Color Temperature in Customize mode for precise color calibration.
	6500K	
	7500K	
	9300K	
	10000K	
	Customize	
	R (0-100)	
	G (0-100)	
	B (0-100)	

Feature	Available Settings	Description
Low Blue Light	OFF	• Low Blue Light protects your eyes against blue light. When enabled, Low Blue Light adjusts the screen color temperature to a more yellow glow. • This monitor is a Low Blue Light monitor which will decrease the blue light emitted without adjusting the OSD settings.
	ON	
Saturation	0-100	• Users can fine-tune the setting values to adjust display saturation.
Six-Axis Color	R (0-100)	• This feature allows users to independently adjust the intensity and saturation of six primary and secondary colors.
	G (0-100)	
	B (0-100)	
	C (0-100)	
	M (0-100)	
	Y (0-100)	
Gamma	Native	• This feature adjusts the midtone brightness of the display without affecting shadows and highlights. • A higher gamma darkens midtones, while a lower gamma brightens them.
	1.8	
	2.0	
	2.2	
	2.4	
	2.6	

Input Source

Feature	Available Settings	Description
HDMI™ 1		• Users can choose their preferred input source.
HDMI™ 2		
DP		
Type C		
Type C PD Charge	OFF	• This function enables users to charge their devices through a USB Type-C connector.
	ON	

Auto Scan	OFF	• Users can use the Navi Key to select Input Source at below status:
		  • While Auto Scan is set to OFF with the monitor at power saving mode;
		  • While No Signal message box is shown on the monitor.

	ON	

PIP/PBP

<table>
<tr><th>Feature</th><th colspan="2">Available Settings</th><th>Description</th></tr>
<tr><td rowspan="15">PIP</td><td colspan="2">OFF</td><td rowspan="15">• PIP (Picture in Picture) allows users to simultaneously display multiple video sources on one screen. One program is displayed on the full screen at the same time as one or more other programs are displayed in inset windows.
• PBP (Picture by Picture) is a similar feature that displays two input sources side-by-side on the screen.
• Display Swap allows users to switch between primary and secondary input sources.
• If there is only one signal input, the Display Swap and Audio Swap will be grayed out.
• Activating PIP/PBP will affect:
<table><tr><th>Affected Function</th><th>Function Status</th></tr><tr><td>» Adaptive-Sync
» Optix Scope</td><td>Set to OFF</td></tr><tr><td>» HDMI™ CEC
» PBP Layout Customize: AI Vision</td><td>Set to OFF & unable to select</td></tr><tr><td>» HDMI™ 2.1
» DSC
» DisplayHDR</td><td>Unable to select</td></tr><tr><td>» Screen Size 1:1
» PBP: Screen Size</td><td>Set to Auto & unable to select</td></tr></table></td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="4">Sub Input</td><td>HDMI™ 1</td></tr>
<tr><td>HDMI™ 2</td></tr>
<tr><td>DP</td></tr>
<tr><td>Type C</td></tr>
<tr><td rowspan="3">Sub Size</td><td>Small</td></tr>
<tr><td>Medium</td></tr>
<tr><td>Large</td></tr>
<tr><td rowspan="2">Sub Ratio</td><td>Auto</td></tr>
<tr><td>Full Screen</td></tr>
<tr><td rowspan="5">Show On</td><td>Left Top</td></tr>
<tr><td>Right Top</td></tr>
<tr><td>Left Bottom</td></tr>
<tr><td>Right Bottom</td></tr>
<tr><td>Customize</td></tr>
<tr><td colspan="2">Display Swap</td></tr>
<tr><td colspan="2">Audio Swap</td></tr>
<tr><td rowspan="11">PBP</td><td colspan="2">OFF</td></tr>
<tr><td colspan="2">ON</td></tr>
<tr><td rowspan="3">PBP Layout</td><td>1:1</td></tr>
<tr><td>3:1</td></tr>
<tr><td>Customize</td></tr>
<tr><td rowspan="4">Sub Input</td><td>HDMI™ 1</td></tr>
<tr><td>HDMI™ 2</td></tr>
<tr><td>DP</td></tr>
<tr><td>Type C</td></tr>
<tr><td colspan="2">Display Swap</td></tr>
<tr><td colspan="2">Audio Swap</td></tr>
</table>

MSI OLED Care

Feature	Available Settings		Description
Pixel Shift	Slow		• Pixel Shift moves the pixels of your screen at regular intervals to reduce the possibility of screen burn-in or image retention.
	Normal		
	Fast		
Panel Protect			• To maintain panel image quality, panel protect function will automatically activate when monitor using over 4 hours. • This protect function may take several minutes to complete. • The power indicator will blink orange color until process done. • During process executing, please do not unplug the power cord from monitor. • During process executing, press power button again to cancel this function.
Panel Notice	Auto		• When set to Auto, Panel Notice will pop up when the panel exceeds 4 hours of cumulative usage. • When set to Usage 24 hrs, Panel Notice will pop up when the panel exceeds 24 hours of cumulative usage. • When Panel Protect is interrupted, Panel Notice will pop up upon next power-up.
	Usage 24 hrs		

Static Screen Detection	OFF		• If Static Screen Detection is set to ON:
			  • When detecting static visuals over long periods of time, the monitor reduces brightness to prevent screen burn-in.
			  • Once detecting moving visuals, the monitor restores its previous brightness setting.

	ON		
	Starting in	50 Sec	• Starting in detects the time a static image remains on the screen.
		100 Sec	
	Time required	120 Sec	• Time required specifies the time for brightness reduction after detecting a static image for 50/100 seconds. • The brightness reduction level depends on the setting of Reducing Level.
		240 Sec	
	Reducing Level	1-7	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness setting.
Multi Logo Detection	OFF		• This function helps prevent image sticking phenomenon. When set to ON, brightness reduction of multi logo areas will kick in if logos are detected.
	ON		
	Reducing Level	1-4	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness setting.

Feature	Available Settings		Description
Multi Icon Detection	OFF		• This function helps prevent image sticking phenomenon. When set to ON, brightness reduction of multi icon areas will kick in if icons are detected.
	ON		
	Reducing Level	1-3	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness/ DisplayHDR setting.
Taskbar Detection	OFF		• This function helps prevent image sticking phenomenon. When set to ON, brightness reduction of taskbar areas will kick in if taskbars are detected.
	ON		
	Reducing Level	1-4	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness setting.
Boundary Detection	OFF		• This function helps prevent image sticking phenomenon. When set to ON, brightness reduction of boundary areas will kick in if boundaries, such as letters & pillars, are detected.
	ON		
	Reducing Level	1-4	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness setting.
V-Split Detection	OFF		• This function helps prevent image sticking phenomenon. When set to ON, brightness reduction along vertical boundaries during multitasking or split-screen gaming will kick in.
	ON		
	Reducing Level	1-4	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness setting.
Auto DIM Control	OFF		• This function prevents image sticking by gradually dimming the screen. When set to ON, it automatically reduces full-screen brightness when detecting static images.
	ON		
	Starting Speed	Slow	• Starting In defines how quickly Auto DIM Control detects a static image.
		Fast	
	Reducing Speed	Slow	• Users can specify the speed for brightness reduction.
		Fast	
	Reducing Level	1-6	• Users can select a level for brightness reduction. • Reducing effect depends on Brightness setting.
OLED Panel Info.			• This field shows the information of MSI OLED Care.

General

Feature	Available Settings		Description
Language	繁體中文		• Users have to press the OK Button to confirm and apply the Language setting. • Language is an independent setting. Users' own language setting will override the factory default. When users set Reset to Yes, Language will not be changed.
	English		
	Français		
	Deutsch		
	Italiano		
	Español		
	한국어		
	日本語		
	Русский		
	Português		
	简体中文		
	Bahasa Indonesia		
	Türkçe		
	(More languages coming soon)		
Power LED	OFF		• Users can toggle the Power LED ON/OFF. • During the Panel Protect process, the power LED indicator will blink orange until the process is complete.
	ON		
Audio	Volume		• Users can adjust Audio in any mode.
	Mute		
RGB LED	OFF		• Users can turn the RGB LED ON or OFF.
	MSI - Mystic Light		
	RGB Brightness		
OSD Menu	OSD Position	Adjust	• This feature adjusts the location of the OSD menu on the screen for user convenience. • Users can adjust OSD Transparency in any mode. • Users can adjust OSD Time Out in any mode.
		Position reset	
	OSD Transparency	0~5	
	OSD Time Out	5~30s	
Ultra Low Power	OFF		• This setting reduces power consumption for more energy-efficient operation.
	ON		

Feature	Available Settings		Description

HDMI™ CEC	OFF		• HDMI™ CEC (Consumer Electronics Control) supports Sony PlayStation®, Nintendo® Switch™, Xbox Series X|S consoles and various audio-visual devices that are CEC-capable.
			• If HDMI™ CEC is set to ON:
			  • The monitor will automatically power on when the CEC device is turned on.
			  • The CEC device will enter power saving mode when the monitor is turned off.
			  • When Sony PlayStation®, Nintendo® Switch™, or Xbox Series X|S console is connected, Mode will be automatically set to the default mode and can be adjusted to users' preferred mode later.

	ON		
Navi Key	Up Down Left Right	OFF	• All Navi Key items can be adjusted via OSD Menus.
		Brightness	
		Mode	
		Input Source	
		AI Crosshair	
		AI Vision	
		Timer	
		Refresh Rate	
		PIP/PBP	
		Optix Scope	
		Info. On Screen	
		Audio Volume	
Info. On Screen	OFF		• The information of the monitor status will be shown in the middle of the screen.
	ON		
Service Info.	FW Version		• View product service details, such as firmware version and serial number, in this setting.
	Serial Number		
Reset All	Yes		• Users can Reset and restore settings to original OSD Default in any mode.
	No		

Specifications*

Monitor	MPG 341CQR QD-OLED X36
Size	34 inch
Curvature	Curve 1800R
Panel Type	QD-OLED
Resolution	3440 x 1440 (UWQHD)
Aspect Ratio	21:9
Brightness	• Typical SDR: 300 nits • Peak HDR: 1300 nits
Contrast Ratio	1500000 : 1
Refresh Rate (Maximum)	360Hz
Response Time	0.03ms (GtG)
I/O	• 1 x Headphone Jack • 2 x HDMI™ Connector • 1 x DisplayPort • 1 x USB Type-C Port • 1 x USB 5Gbps Type-B Upstream Port • 2 x USB 5Gbps Type-A Port
View Angles	178°(H) , 178°(V)
DCI-P3** / sRGB	99%/ 139.1%
Surface Treatment	Anti-Reflection
Display Colors	1.07B, 10 bits
Monitor Power Options	100-240 V~, 50/60Hz, 2.9 A
Power Consumption (Typical)	Power On < 250 W Standby < 0.5 W Power Off < 0.3 W
Adjustment (Height)	0 ~ 110 mm
Adjustment (Tilt)	-5° ~ 15°
Adjustment (Swivel)	-30° ~ 30°
Adjustment (Pivot)	-10° ~ 10°
Kensington Lock	Yes

Monitor		MPG 341CQR QD-OLED X36

VESA Mounting		• Plate Type: 100 x 100 mm
		• Screw Type: M4 x 10 mm
		  • Thread Diameter: 4 mm
		  • Thread Pitch: 0.7 mm
		  • Thread Length: 10 mm

Dimension (W x D x H)		812.8 x 228.3 x 543.1 mm
Weight	Net	7.77 kg
	Gross	13.49 kg
Operating Environment		• Temperature: 0°C to 40°C • Humidity: 20% to 90%, non-condensing • Altitude: 0 ~ 5000m
Storage Environment		• Temperature: -20°C to 60°C • Humidity: 10% to 90%, non-condensing

* Some technical specifications of the device may be subject to change by the manufacturer. Please verify the specifications with the seller or the manufacturer's representative.

** Based on CIE1976 test standards.

Preset Display Modes

Important

- *All information is subject to change without prior notice.*
- *HDMI™ VRR (Variable Refresh Rate) synchronizes with Adaptive-Sync (ON/ OFF). For VRR ON/OFF status, please check Adaptive-Sync.*
- *To activate DSC-specific timing and frequency, ensure your graphics card supports DSC (Display Stream Compression).*

HDMI™ 2.1 - PC, DSC ON

Standard	Resolution		HDMI™	DP	USB-C
QHD	2560x1440	@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz		V	V
		@360Hz	V	V	V
QHD+	3440x1440	@50Hz	V		
		@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz	V	V	V
		@360Hz	V	V	V
Video Timing Resolution	720P		V	V	V
	1080P	@60Hz	V	V	V
		@120Hz	V	V	V
	2560x1080p	@60Hz	V	V	V
		@120Hz	V	V	V
HDMI™ VRR			V		

HDMI™ 2.1 - PC, DSC OFF

Standard	Resolution		HDMI™	DP	USB-C
QHD	2560x1440	@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz	V	V	V
QHD+	3440x1440	@50Hz	V		
		@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz	V	V	V
Video Timing Resolution	720P		V	V	V
	1080P	@60Hz	V	V	V
		@120Hz	V	V	V
	2560x1080p	@60Hz	V	V	V
		@120Hz	V	V	V
HDMI™ VRR			V		

HDMI™ 2.1 - Console, DSC ON

Standard	Resolution		HDMI™	DP	USB-C
QHD	2560x1440	@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz		V	V
		@360Hz	V	V	V
QHD+	3440x1440	@50Hz	V		
		@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz	V	V	V
		@360Hz	V	V	V
Video Timing Resolution	720P		V	V	V
	1080P	@60Hz	V	V	V
		@120Hz	V	V	V
	2160P	@30Hz	V		
		@60Hz	V		
		@120Hz	V		
	2560x1080p	@60Hz	V	V	V
		@120Hz	V	V	V
HDMI™ VRR			V		

HDMI™ 2.1 - Console, DSC OFF

Standard	Resolution		HDMI™	DP	USB-C
QHD	2560x1440	@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz	V	V	V
QHD+	3440x1440	@50Hz	V		
		@60Hz	V	V	V
		@120Hz	V	V	V
		@240Hz	V	V	V
Video Timing Resolution	720P		V	V	V
	1080P	@60Hz	V	V	V
		@120Hz	V	V	V
	2160P	@30Hz	V		
		@60Hz	V		
		@120Hz	V		
	2560x1080p	@60Hz	V	V	V
		@120Hz	V	V	V
HDMI™ VRR			V		

PIP Mode (Not Support HDR)

Standard	Resolution		HDMI™	DP	USB-C
QHD	2560x1440	@60Hz	V	V	V
		@120Hz	V	V	V
QHD+	3440x1440	@50Hz	V		
		@60Hz	V	V	V
		@120Hz	V	V	V
Video Timing Resolution	720P		V	V	V
	1080P	@60Hz	V	V	V
		@120Hz	V	V	V
	2160P	@30Hz	V	V	
		@50Hz	V	V	
		@60Hz	V	V	

PBP Mode 3:1 (Not Support HDR)

Standard	Resolution		HDMI™	DP	USB-C
Video Timing Resolution	720P		V	V	V
Used for PBP Full Screen	880x1440	@60Hz	V	V	V
	2560x1440	@60Hz	V	V	V

PBP 1:1/Customize (Not Support HDR)

Standard	Resolution		HDMI™	DP	USB-C
Video Timing Resolution	720P		V	V	V
Used for PBP Full Screen	1720x1440	@60Hz	V	V	V

Troubleshooting

The power LED is off.

- Press the monitor power button again.
- Check if the monitor power cable is properly connected.

No image.

- Check if the computer graphics card is properly installed.
- Check if the computer and monitor are connected to electrical outlets and are turned on.
- Check if the monitor signal cable is properly connected.
- The computer may be in Standby mode. Press any key to activate the monitor.

The screen image is not properly sized or centered.

- Refer to Preset Display Modes to set the computer to a setting suitable for the monitor to display.

No Plug & Play.

- Check if the monitor power cable is properly connected.
- Check if the monitor signal cable is properly connected.
- Check if the computer and graphics card are Plug & Play compatible.

The icons, font or screen are fuzzy, blurry or have color problems.

- Avoid using any video extension cables.
- Adjust brightness and contrast.
- Adjust RGB color or tune color temperature.
- Check if the monitor signal cable is properly connected.
- Check for bent pins on the signal cable connector.

The monitor starts flickering or shows waves.

- Change the refresh rate to match the capabilities of your monitor.
- Update your graphics card drivers.
- Keep the monitor away from electrical devices that may cause electromagnetic interference (EMI).

Safety Instructions

- Read the safety instructions carefully and thoroughly.
- All cautions and warnings on the device or User Guide should be noted.
- Refer servicing to qualified personnel only.

Power

- Make sure that the power voltage is within its safety range and has been adjusted properly to the value of 100~240V before connecting the device to the power outlet.
- If the power cord comes with a 3-pin plug, do not disable the protective earth pin from the plug. The device must be connected to an earthed mains socket-outlet.
- Please confirm the power distribution system in the installation site shall provide the circuit breaker rated 120/240V, 20A (maximum).
- Always disconnect the power cord or switch the wall socket off if the device would be left unused for a certain time to achieve zero energy consumption.
- Place the power cord in a way that people are unlikely to step on it. Do not place anything on the power cord.
- If this device comes with an adapter, use only the MSI provided AC adapter approved for use with this device.

Environment

- To reduce the possibility of heat-related injuries or of overheating the device, do not place the device on a soft, unsteady surface or obstruct its air ventilators.
- Use this device only on a hard, flat and steady surface.
- To prevent the device from tipping over, secure the device to a desk, wall or fixed object with an anti-tip fastener that helps to properly support the device and keep it safe in place.
- To prevent fire or shock hazard, keep this device away from humidity and high temperature.
- Do not leave the device in an unconditioned environment with a storage temperature above 60°C or below -20°C, which may damage the device.
- The maximum operating temperature is around 40°C.
- When cleaning the device, be sure to remove the power plug. Use a piece of soft cloth rather than industrial chemical to clean the device. Never pour any liquid into the opening; that could damage the device or cause electric shock.
- Always keep strong magnetic or electrical objects away from the device.

- If any of the following situations arises, get the device checked by service personnel:
  - The power cord or plug is damaged.
  - Liquid has penetrated into the device.
  - The device has been exposed to moisture.
  - The device does not work well or you can not get it working according to the User Guide.
  - The device has dropped and damaged.
  - The device has obvious sign of breakage.

TÜV Rheinland Certification

TÜV Rheinland Low Blue Light Certification

Blue light has been shown to cause eye fatigue and discomfort. MSI now offers monitors with TÜV Rheinland Low Blue Light certification to ensure users' eye comfort and well-being. Please follow the instructions below to reduce the symptoms from extended exposure to the screen and blue light.



- Place the screen 20 – 28 inches (50 – 70 cm) away from your eyes and a little below eye level.
- Consciously blinking the eyes every now and then will help to reduce eye strain after extended screen time.
- Take breaks for 20 minutes every 2 hours.
- Look away from the screen and gaze at a distant object for at least 20 seconds during breaks.
- Make stretches to relieve body fatigue or pain during breaks.

TÜV Rheinland Flicker Free Certification



- TÜV Rheinland has tested this product to ascertain whether the display produces visible and invisible flicker for the human eye and therefore strains the eyes of users.
- TÜV Rheinland has defined a catalogue of tests, which sets out minimum standards at various frequency ranges. The test catalogue is based on internationally applicable standards or standards common within the industry and exceeds these requirements.
- The product has been tested in the laboratory according to these criteria.
- The keyword "Flicker Free" confirms that the device has no visible and invisible flicker defined in this standard within the range of 0 - 3000 Hz under various brightness settings.
- The display will not support Flicker Free when Anti Motion Blur/MPRT is enabled. (The availability of Anti Motion Blur/MPRT varies by products.)

Regulatory Notices

CE Conformity

This product has been tested and found to comply with the harmonized standards for Information Technology Equipment published under Directives of Official Journal of the European Union.

FCC-B Radio Frequency Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the measures listed below:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/television technician for help.

Notice 1

The changes or modifications not expressly approved by the party responsible for compliance could void the user' s authority to operate the equipment.

Notice 2

Shielded interface cables and AC power cord, if any, must be used in order to comply with the emission limits.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

MSI Computer Corp.

901 Canada Court, City of Industry, CA 91748, USA

(626) 913-0828

www.msi.com

WEEE Statement



European Union: This symbol on the product indicates that this product cannot be discarded as municipal waste. Instead, it is your responsibility to dispose of your waste electrical and electronic equipment by handing it over to a designated collection point for recycling. For more information about where you can drop off your waste equipment for recycling, please contact your local city office, your household waste disposal service or the shop where you purchased the product.

Chemical Substances Information

In compliance with chemical substances regulations, such as the EU REACH Regulation (Regulation EC No. 1907/2006 of the European Parliament and the Council), MSI provides the information of chemical substances in products at:
https://csr.msi.com/global/index

RoHS Statement

Japan JIS C 0950 Material Declaration

A Japanese regulatory requirement, defined by specification JIS C 0950, mandates that manufacturers provide material declarations for certain categories of electronic products offered for sale after July 1, 2006.
https://csr.msi.com/global/Japan-JIS-C-0950-Material-Declarations

India RoHS

This product complies with the "India E-waste (Management and Handling) Rule 2016" and prohibits use of lead, mercury, hexavalent chromium, polybrominated biphenyls or polybrominated diphenyl ethers in concentrations exceeding 0.1 weight % and 0.01 weight % for cadmium, except for the exemptions set in Schedule 2 of the Rule.

Turkey EEE Regulation

Conforms to the EEE Regulations of the Republic Of Turkey

Ukraine Restriction of Hazardous Substances

The equipment complies with requirements of the Technical Regulation, approved by the Resolution of Cabinet of Ministry of Ukraine as of 10 March 2017, № 139, in terms of restrictions for the use of certain dangerous substances in electrical and electronic equipment.

Vietnam RoHS

As from December 1, 2012, all products manufactured by MSI comply with Circular 30/2011/TT-BCT temporarily regulating the permitted limits for a number of hazardous substances in electronic and electric products.

Green Product Features

- Reduced energy consumption during use and stand-by
- Limited use of substances harmful to the environment and health
- Easily dismantled and recycled
- Reduced use of natural resources by encouraging recycling
- Extended product lifetime through easy upgrades
- Reduced solid waste production through take-back policy

Environmental Policy



- The product has been designed to enable proper reuse of parts and recycling and should not be thrown away at its end of life.
- Users should contact the local authorized point of collection for recycling and disposing of their end-of-life products.
- Visit the MSI website <https://csr.msi.com/global/pevn_ewaste> and locate a nearby distributor for further recycling information.
- Please visit <https://us.msi.com/page/recycling> for information regarding the recycling of your product in the US.

Warning!

Overuse of screens is likely to affect eyesight.

Recommendations:

1. Take a 10-minute break for every 30 minutes of screen time.
2. Children under 2 years of age should have no screen time. For children aged 2 years and over, screen time should be limited to less than one hour per day.

Copyright and Trademarks Notice

Copyright © Micro-Star Int' l Co., Ltd. All rights reserved. The MSI logo used is a registered trademark of Micro-Star Int' l Co., Ltd. All other marks and names mentioned may be trademarks of their respective owners. No warranty as to accuracy or completeness is expressed or implied. MSI reserves the right to make changes to this document without prior notice.

The terms HDMI™, HDMI™ High-Definition Multimedia Interface, HDMI™ Trade dress and the HDMI™ Logos are trademarks or registered trademarks of HDMI™ Licensing Administrator, Inc.

Technical Support

If a problem arises with your product and no solution can be obtained from the user' s manual, please contact your place of purchase or local distributor. Alternatively, please visit https://www.msi.com/support/ for further guidance.

tehnoteka

https://cenoteka.rs

Ovaj dokument je originalno proizveden i objavljen od strane proizvođača, brenda MSI, i preuzet je sa njihove zvanične stranice. S obzirom na ovu činjenicu, Cenoteka ističe da ne preuzima odgovornost za tačnost, celovitost ili pouzdanost informacija, podataka, mišljenja, saveta ili izjava sadržanih u ovom dokumentu.

Napominjemo da Cenoteka nema ovlašćenje da izvrši bilo kakve izmene ili dopune na ovom dokumentu, stoga nismo odgovorni za eventualne greške, propuste ili netačnosti koje se mogu naći unutar njega. Cenoteka ne odgovara za štetu nanesenu korisnicima pri upotrebi netačnih podataka. Ukoliko imate dodatna pitanja o proizvodu, ljubazno vas molimo da kontaktirate direktno proizvođača kako biste dobili sve detaljne informacije.

Za najnovije informacije o ceni, dostupnim akcijama i tehničkim karakteristikama proizvoda koji se pominje u ovom dokumentu, molimo posetite našu stranicu klikom na sledeći link:

https://cenoteka.rs/p/msi-zakrivljeni-monitor-34-mpg-341cqr-qd-oled-x36/